

### HE910 information and available service for each USB interfaces

Port	VID	PID	Interface Number	Transfer type	Number of Endpoint	Endpoint Address	Serial Emulation	Available Service
MDM - ACM0	0x1BC7	0x0021	0	Interrupt	1	0x81	v	DATA (high speed) /ATC
			1	bulk[512]	2	0x82 0x02		DATA (high speed) /ATC
Telit Diagnostic Interface - ACM1			2	interrupt	1	0x83		TRACE
			3	bulk[512]	2	0x84 0x04		TRACE
Telit NMEA Port - ACM2			4	Interrupt	1	0x85		NMEA Data
			5	Bulk[512]	2	0x86 0x06		NMEA Data
Auxiliary Port - ACM3			6	Interrupt	1	0x87	v	DATA (high speed) /ATC
			7	Bulk[512]	2	0x88 0x08		DATA (high speed) /ATC
ACM4			8	Interrupt	1	0x89		Not used
			9	Bulk[512]	2	0x8a 0x0a		Not used
ACM5			10	Interrupt	1	0x8b		Not used
			11	Bulk[512]	2	0x8c 0x0c		Not used
ACM6			12	Interrupt	1	0x8d		Not used
	13	Bulk[512]	2	0x8e 0x0e		Not used		

Below a description for HE910:

bLength	9 (0x09)
bDescriptorType	CONFIGURATION (0x02)
wTotalLength	415 (0x19f)
bNumInterfaces	14 (0x0e)
bConfigurationValue	1 (0x01)
iConfiguration	(0x00)
bmAttributes.Reserved1	0x1
bmAttributes.SelfPowered	Self Powered (0x1)
bmAttributes.RemoteWakeup	Supported (0x1)
bmAttributes.Reserved0	0x00
bMaxPower	100mA (0x32)